

# NEOLINE PLUS

## 1-10kVA ONLINE UPS

Υψηλής απόδοσης μονοφασικά ON-LINE UPS με αντιστροφέα (inverter) τεχνολογίας διπλής μετατροπής και συντελεστή ισχύος εξόδου 0.9. Παρέχουν άριστη προστασία για τα κρίσιμα φορτία, εξαλείφοντας όλες τις διαταραχές του ρεύματος. Με μηδενικό χρόνο μεταγωγής, καθαρή ημιτονική τάση στην έξοδο και δυνατότητα υποστήριξης διαφορετικών φορτίων, είναι η βέλτιστη λύση για ασφάλεια στο σπίτι, υποστήριξη μηχανογραφικών εφαρμογών, κάλυψη παθητικού εξοπλισμού αλλά και ιατρικών μηχανημάτων.

*1 phase in / 1 phase out*



### ENHANCED POWER PROTECTION



TELECOM



SERVERS



LIGHT  
INDUSTRY



SECURITY



OFFICE  
COMPUTERS



NAVAL  
ELECTRONICS



MEDICAL  
APPLICATIONS

## ΤΕΧΝΙΚΑ ΧΑΡΑΚΤΗΡΙΣΤΙΚΑ

- Τεχνολογία πραγματικής διπλής μετατροπής
- Έλεγχος με μικροεπεξεργαστή που βελτιστοποιεί την αξιοπιστία του συστήματος
- Διόρθωση συντελεστή ισχύος εισόδου
- Συντελεστής ισχύος εξόδου 0.9
- Μεγάλο εύρος τάσης εισόδου (120V - 300V)
- Λειτουργία μετατροπέα
- Λειτουργία ECO για εξοικονόμηση ενέργειας (1-3KVA)
- Συμβατό με γεννήτρια
- Θύρες Smart USB/RS-232, SNMP (προαιρετικά)
- LCD οθόνη που επιτρέπει την εύκολη παρακολούθηση του UPS
- Αυτόματη επανεκκίνηση
- Ψυχρή εκκίνηση
- Θύρα EPO (Emergency Power Off) (6-10kVA)
- Αλλαγή μπαταριών εν θερμώ

# NEOLINE PLUS

ONLINE UPS *1 phase in / 1 phase out* 1-3 kVA



MODEL	Neoline Plus 1101ST		Neoline Plus 1102ST		Neoline Plus 1103ST		
TESCOM CODE	UPS.0404		UPS.0405		UPS.0406		
PHASE	Single phase with ground						
CAPACITY	1000 VA / 900 W		2000 VA / 1800 W		3000 VA / 2700 W		
<b>INPUT</b>							
Nominal Voltage	200/208/220/230/240VAC						
Voltage Range	120-300 VAC (Based on load at 50%) 180-280 VAC (Based on load at 100%)						
Frequency Range	40Hz ~ 70 Hz						
Power Factor	≥ 0.99 @ Nominal Voltage (100% load)						
<b>OUTPUT</b>							
Output Voltage	110/115/120/127VAC or 200/208/220/230/240VAC						
Voltage Regulation	± 1%						
Frequency Range (Synchronized Range)	47~ 53 Hz or 57 ~ 63 Hz						
Frequency Range (Batt. Mode)	50 Hz or 60Hz ± 0.5%						
Current Crest Ratio	3:1						
Harmonic Distortion	≤ 3 % THD (Linear Load)						
Transfer Time	AC Mode to Battery Mode	Zero					
	Inverter to Bypass	4 ms (Typical)					
Waveform (Batt. Mode)	Pure Sinewave						
Overload AC mode	105-110%: 10 min / 110-130%: 1 min / >130%: 3 sec to 100ms						
Outlets (Πρίζες)	3 Schuko			4 Schuko / Output Terminal			
<b>EFFICIENCY</b>							
To AC Mode	88%		89%		90%		
To Battery Mode	83%		85%		88%		
<b>BATTERY</b>							
Standard Model	Battery Type	12 V / 9 AH		12 V / 9 AH		12 V / 9 AH	
	Numbers	2		4		6	
	Typical Recharge Time	4 hours recover to 90% capacity					
	Charging Current (max.)	1.0 A					
	Charging Voltage	27.4VDC ± 1%		54.7 VDC ±1%		82.1 VDC ±1%	
<b>INDICATORS</b>							
LCD	Load level, Battery level, AC mode, Battery mode, Bypass mode, and Fault indicators						
<b>ALARM</b>							
Battery Mode	Alarm Sound / 4 Seconds						
Low Battery	Alarm Sound / Second						
Overload	2 Alarm Sounds / Second						
Fault	Continuous Alarm Sound						
<b>PHYSICAL</b>							
Standard Model	Dimension, D x W x H (mm)	282 x 145 x 220		397 x 145 x 220		421 x 190 x 318	
	Net Weight (kgs)	9,8		17		27,6	
<b>ENVIRONMENT</b>							
Humidity	20-90 % RH @ 0- 40°C (non-condensing)						
Noise Level	Less than 50dBA @ 1 Meter						
<b>MANAGEMENT</b>							
Smart RS-232/USB	Supports Windows 2000/2003/XP/Vista/2008/7/8, Linux, Unix, and MAC						
Optional SNMP	Power management from SNMP manager and web browser						

\*1-3KVA: De-rate to 80% of capacity in Frequency converter mode and to 80% when the output voltage is adjusted to 100/200/208VAC  
Product specifications are subject to change without further notice

# NEOLINE PLUS

ONLINE UPS *1 phase in / 1 phase out* 6-10 kVA



MODEL	Neoline Plus 1106ST		Neoline Plus 1110ST		Neoline Plus 1106ST XL	Neoline Plus 1110ST XL	
TESCOM CODE	UPS.0360	UPS.0552	UPS.0414	UPS.0617	UPS.0362	UPS.0426	
PHASE	Single phase with ground						
CAPACITY	6000 VA / 5400 W		10000 VA / 9000 W		6000 VA / 5400 W	10000 VA / 9000 W	
<b>INPUT</b>							
Nominal Voltage	208/220/230/240VAC						
Voltage Range	110-300 VAC (Based on load at 50%) 176-300 VAC (Based on load at 100%)						
Frequency Range	46~54 Hz or 56~64 Hz						
Power Factor	≥ 0.99 @ Nominal Voltage (100% load)						
<b>OUTPUT</b>							
Output Voltage	208/220/230/240VAC						
Voltage Regulation	± 1%						
Frequency Range (Synchronized Range)	46~54 Hz or 56~64 Hz						
Frequency Range (Batt. Mode)	50 Hz or 60Hz ± 0.1 Hz						
Current Crest Ratio	3:1						
Harmonic Distortion	≤ 3 % THD (Linear Load)						
Transfer Time	AC Mode to Battery Mode	Zero					
	Inverter to Bypass	Zero					
Waveform (Batt. Mode)	Pure Sinewave						
<b>EFFICIENCY</b>							
To AC Mode	92%		93%		92%	93%	
To Battery Mode	90%		91%		90%	91%	
<b>BATTERY</b>							
Standard Model	Battery Type	12 V / 7 AH	12 V / 9 AH	12 V / 9 AH		Depending on the capacity of external batteries	
	Numbers	16	20	16	20	16 ~ 20 (Adjustable)	
	Typical Recharge Time	9 hours recover to 90% capacity		9 hours recover to 90% capacity		Depending on the capacity of external batteries	
	Charging Current (max.)	1A/2A (Adjustable)		1A/2A (Adjustable)			
	Charging Voltage	218.4 VDC ±1%	273 VDC ±1%	218.4 VDC ±1%	273 VDC ±1%	273 VDC ±1% (Based on 20pcs batteries)	
<b>INDICATORS</b>							
LCD	Load level, Battery level, AC mode, Battery mode, Bypass mode, and Fault indicators						
<b>ALARM</b>							
Battery Mode	Alarm Sound / 4 Seconds						
Low Battery	Alarm Sound / Second						
Overload	2 Alarm Sounds / Second						
Fault	Continuous Alarm Sound						
<b>PHYSICAL</b>							
Standard Model	Dimension, D x W x H (mm)	369 x 190 x 688	442 x 190 x 688	442 x 190 x 688		369 x 190 x 318	442 x 190 x 318
	Net Weight (kgs)	61	74	66	76	12	16
<b>ENVIRONMENT</b>							
Humidity	0-95% RH @ 0-40°C (non-condensing)						
Noise Level	Less than 55dBA @ 1 Meter		Less than 58dBA @ 1 Meter		Less than 55dBA @ 1 Meter	Less than 58dBA @ 1 Meter	
<b>MANAGEMENT</b>							
Smart RS-232/USB	Supports Windows 2000/2003/XP/Vista/2008/7/8, Linux, Unix, and MAC						
Optional SNMP	Power management from SNMP manager and web browser						

\*6-10KVA: De-rate to 60% of capacity in Frequency converter mode and to 90% when the output voltage is adjusted to 208VAC  
Product specifications are subject to change without further notice